

## Настройка телефонов D-Link DPH-150SE для работы с услугой «Мультифон»

Для регистрации учетной записи необходимо зайти в настройки телефонного аппарата через WEB-интерфейс. В меню «VOIP»

выбрать необходимую линию и заполнить следующие поля:

- в поля «Account Name», «Display Name», «Proxy Username» необходимо внести номер телефона, указанный при регистрации в услуге Мультифон
- в поле «Password» необходимо внести пароль указанный при регистрации учетной записи
- в поля «Server Name» и «Server Address» необходимо внести «multifon.ru»
- в поле «Proxy Server Address» указать «sbc.megafon.ru»
- в поле «Proxy Server Port» необходимо внести «5060»

Firmware Version: GE\_1.00

**D-Link**

DPH-150SE // BASIC NETWORK **VOIP** PHONE MAINTENANCE SECURITY LOGOUT

SIP  
Stun  
Dial Peer

SIP Line Select  
SIP 1 Load

Basic Setting

Register Status:	Registered	Display Name:	79260000001
Server Name:	multifon.ru	Proxy Server Address:	sbc.megafon.ru
Server Address:	multifon.ru	Proxy Server Port:	5060
Server Port:	5060	Proxy Username:	79260000001
Account Name:	79260000001	Proxy Password:	
Password:	*****	Domain Realm:	
Phone Number:	79260000001	Enable Register:	<input checked="" type="checkbox"/>

APPLY  
Advanced Set

BROADBAND

Copyright © 2010 D-Link International Pte. Ltd.